TRX2S 用 OpenCPN USB 接続方法

<準備>

OpenCPN をインストールした PC を TRX2S と USB 接続してください。(TRX2S は電源 を入れている状態で問題ございません。) OpenCPN に CM93 という海図データを読み込ん でチャートの詳細が表示されます。CM93 を希望の方は弊社 TRX2S のサポートとして、無 償で提供しております。

<OpenCPN 設定>

OpenCPN を起動します。左上のツールバーの Option (設定)クリックします。



Option 画面が表示されます。

①設定画面の Connections(接続)クリックします。

②Add Connections(追加接続)を選択して、接続の追加設定を行います。

(a) Serial (シリアル) 選択
(b) Dataport (ポート) から PC に 接続されているデータポートを選 択してください。(ポート番号が不 明の場合は、デバイスマネージャ よりご確認ください。)
(c) Baudrate (ボートレート) を 38400 を選択します。

③Apply (適用)をクリックし、次にのKをクリックして設定を完了してください。。

以上で TRX2S と OpenCPN が接 続がされ、OpenCPN に受信した 他船の船舶が表示されます。

		01	妾続			~	
Display	Charts	Connections	Ships	User	tt) Interface	Plugins	1
N <						>	Att
General						^	
Filter NMEA	Course and Speed da Debug Window ads for Furuno GP3X GRMN (Host) mode fo	ta Filter period (sec r uploads	0 [1				
Data Connection	ic bearings in output s is	entence ECAPB					-
Enable Type	DataPort ork 10.10.100.254:88	Priority Param	eters Connection Input	Filters In: None, Out: I	lone		
A ②追加接 Add Connectin	新来 192,108,16,2543 続 の Bernow Coone	1080 1 1CP	Input	In: None, Out: 1	vone	_	
Add Connective Add Connective Properties (a) Properties (b) (c) DetaPort Protocol Control che Control che		(b) Baudrate <u>38400</u> Priority <u>1</u> se Garmin (GRMN) mo utput on this port (as	input	In: None, Out: /	vone ::		
Add Connective Add Connective Add Connective Properties Serial DetaFort Protocol Control che Receive top Taker 10 doin	Network USB Senal Port Statum Us on this Port Conne	(b) Baudrate <u>38400</u> Priority <u>1</u> se Germin (GRMN) mo utput on this port (as a	(c) de for input sutopilot or NMEA	In: None, Out: /	wone -		
Add Connective Add Connective Properties (a) DetaPort Protocol DetaPort Protocol Control che Taker 10 datan APb besiring pr	A 192,108,10,204,3 A A A A A A A A A A A A A A A A A A	(b) Baudrate <u>38400</u> Priority <u>1</u> se Garmin (GRMN) mo utput on this port (as	(c) (c) (de for input autopriot or NMEA	In: None, Out: /	wone:	↓ 3 <i>遭</i> 月	Ħ
Add Connectin Add Connectin Properties Add Connectin Protector Protocol Control che Control che Contr		(b) Baudrate <u>18400</u> Priority <u>1</u> se Garmin (GRMN) mo utput on this port (as	input (6) de for input sutopilot or NMEA	repeater)	Cancel	↓ 3適用 Apply	Ħ

実際の OpenCPN 受信画面は下記となります。

※GPS で自分の位置を受信した船船舶の場合は船のマークになります。(赤のマーク)



(オプションなどの追加) オンラインショップでご購入ください 船長さんの無線ショップ HP:www.ais-japan.org

> (お問合せ・故障などサービス) メール: shop@ais-japan.org

